

# SMART AMP RECEIVER



The NuBryte Smart Amplifier enables robust and rich sound in both passive speakers and traditional amplified systems, without all the extra wiring.

Our new Wi-Fi amp works perfectly with a built-in WiSA receiver and two 50W amplifiers to power passive speakers. It also allows for easy installation that connects it to an available power source in the ceiling or wall.



**Wi-Fi Streaming**  
Connect to local Wi-Fi for audio streaming.



**Simplify Installs**  
Power speakers without running cable from source.



**App Ready**  
Use the NuBryte mobile app or Airplay for instant setup.



**Spotify Ready**  
Spotify, Airplay, DLNA & Wifi-Direct plus many more.

## PRODUCT SPECIFICATIONS

<b>Output Power</b>	2 x 50Wrms @ 4ohm. 2 x 25Wrms @ 8ohm.
<b>THD</b>	<1%.
<b>Frequency Response</b>	20Hz - 20KHz.
<b>S/N Ratio</b>	>90dB at rated power.
<b>Inputs/ Outputs</b>	Wi-Fi, RCA & Toslink. Optional IR remote. 1 x stereo amp output, AC jack.
<b>LED Indicators</b>	2 x Status LED & Segment LED for channel selection.
<b>Working Voltage</b>	100-240V AC, 50-60Hz.
<b>Color/ Finish</b>	Brushed Aluminum.



Stream music and control audio from NuBryte Touchpoint and Mobile App